

Quick Page Commands

See Also: [RDR Programming Commands](#),
[RDR Over-The-Air \(OTA\) Commands](#),
[RDR Test Mode](#), [Portable Radio Commands](#).

QUICK PAGE

The quick page feature is factory enabled and provides the capabilities to use quick commands from a portable radio to operate the RDR system. These commands include the following:

- q Station Turn On.
- q Station Shutdown.
- q RDR Re-address.
- q Increment/Decrement Syringe System.

Station Turn On

The following command sequence is used to turn on RDR stations:

Portable Command	People Finder Response from Command
*900175110103	Sends message to turn on stations 1 and 3 in RDR field satellite number 001 (no voice prompts necessary).
or	
*9001	'enter command'
75110103	Sends message to turn on stations 1 and 3 in RDR field box number 001.
or	
*9	'enter address'
00175110103	Sends message to turn on stations 1 and 3 in RDR field box number 001.

Station Shutdown

The all station shut down command is used to shut down all stations currently activated in a particular RDR field unit. This feature can be user configured and enabled or disabled using the People Finder keypad. Enable the feature as follows:

With the People Finder in the 'standby' state, perform the following procedure:

Station Shutdown Enable Procedure

Action	Result
On the People Finder keypad, press the '-' key.	People Finder displays 'PASSWORD =' followed by a flashing prompt.
On the People Finder keypad, enter 7531. Enter number by pressing the F1 key.	People Finder steps through the eight available options.
Press the number '8' key.	People Finder displays 'QUICK SHUT?' followed by a 'Y' or 'N'.
Toggle to 'Y' with any numbered key, then press the '-' key two times.	Procedure is complete and feature is enabled.

Once this feature is enabled, it may be activated from a portable radio by sending a * '4' command. The People Finder responds to this by immediately sending out a 7540 command to the RDR last addressed.

If the last address was a 256 group call address, the RDR's will shut down in a controlled manner to prevent damage from any abrupt pressure changes.

RDR Re-address

This feature allows the user to not re-enter the satellite address for subsequent commands sent to the same RDR unit. The quick page process for this feature is as follows:

RDR Re-Address Procedure

Action	Result
From a portable radio, send '*9', unit address, and command to the People Finder.	People Finder sends the command to the RDR.
To send additional commands enter '*0' followed by a new command.	People Finder sends the command to the RDR most recently addressed.